

33210A 10 MHz Function/Arbitrary Waveform Generator

Uncompromising Performance at an Affordable Price

The Keysight Technologies, Inc. 33210A function/arbitrary waveform generator is the latest addition to the 332XX family. Waveforms are generated using direct digital synthesis (DDS) technology which creates stable, accurate low distortion sine waves as well as square waves with fast rise and fall times up to 10 MHz and linear ramp waves up to 100 kHz. For user defined waveforms, Option 002 provides 14-bit, 50 MSa/s 8K point arbitrary waveform generation.

Pulse generation

The 33210A can generate variable-edge-time pulses up to 5 MHz. With variable period, pulse width, and amplitude the 33210A is ideally suited to a wide variety of applications requiring a flexible pulse signal.



Key features

- 10 MHz Sine and Square waveforms
- Pulse, Ramp, Triangle, Noise, and DC waveforms
- Optional 14-bit, 50 MSa/s, 8K point Arbitrary Waveform Generator
- AM, FM, and PWM modulation types
- Linear and logarithmic sweeps and burst operation
- 10 mVpp to 10 Vpp amplitude range
- Graph mode for visual verification of signal settings
- Connect via USB, GPIB and LAN
- Fully compliant to LXI Class C specification

Custom waveform generation (Option 002)

The optional 8K point arbitrary waveform generator (Option 002) can be used in the 33210A to generate complex custom waveforms. With 14-bit resolution, and a sampling rate of 50 MSa/s, the 33210A gives you the flexibility to create the waveforms you need. It also lets you store up to four waveforms in nonvolatile memory. The Keysight IntuiLink arbitrary waveform software allows you to easily create, edit, and download complex waveforms using the waveform editor. Or you can capture a waveform using IntuiLink for Oscilloscopes and send it to the 33210A for output. To find out more about IntuiLink, visit www.keysight.com/find/intuilink

Easy-to-use functionality

Front-panel operation of the 33210A is straight-forward and user friendly. You can access all major functions with a single key or two. The knob or numeric keypad can be used to adjust frequency, amplitude, offset, and other parameters. You can even enter voltage values directly in Vpp, Vrms, dBm, or as high and low levels. Timing parameters can be entered in Hertz (Hz) or seconds.

Internal AM, FM, and PWM modulation make it easy to modulate waveforms without the need for a separate modulation source. Linear and logarithmic sweeps are also built in, with sweep rates selectable from 1 ms to 500 s. Burst mode operation allows for a user-selected number of cycles per trigger. GPIB, LAN, and USB interfaces are all standard, plus you get full programmability using SCPI commands.

External frequency reference (Option 001)

The 33210A external frequency reference lets you synchronize to an external 10 MHz clock, to another 33210A, or to a Keysight 33220A or Keysight 33250A. Phase adjustments can be made from the front panel or via a computer interface, allowing precise phase calibration and adjustment.

Measurement Characteristics

Waveforms

Standard	Sine, Square, Ramp, Triangle, Pulse, Noise, DC
Built-in arbitrary waveforms (available only with Option 002 ARB)	Exponential rise, Exponential fall, Negative ramp, Sin(x)/x, Cardiac

Waveform characteristics

Sine		
Frequency range	1 mHz to 10 MHz	
Amplitude flatness ^{1,2} (relative to 1 kHz)	< 100 kHz	0.1 dB
	100 kHz to 5 MHz	0.2 dB
	5 MHz to 10 MHz	0.3 dB
Harmonic distortion (typ) ^{2,3}	< 1 Vpp	≥ 1 Vpp
DC to 20 kHz	-70 dBc	-70 dBc
20 kHz to 100 kHz	-65 dBc	-60 dBc
100 kHz to 1 MHz	-50 dBc	-45 dBc
1 MHz to 10 MHz	-40 dBc	-30 dBc
Total harmonic distortion (typ) ^{2,3}	DC to 20 kHz	0.04%
	DC to 1 MHz	-70 dBc
Spurious (non-harmonic) (typ) ^{2,4}	1 MHz to 10 MHz	-70 dBc + 6 dB/octave
	Phase noise (10 kHz offset) (typ)	-115 dBc / Hz
Square		
Frequency range	1 mHz to 10 MHz	
Rise/fall time	20 ns	
Overshoot	< 2%	
Variable duty cycle	20% to 80% (to 5 MHz)	
	40% to 60% (to 10 MHz)	
Asymmetry (at 50% duty)	1% of period + 5 ns	
Jitter (RMS)	1 ns + 100 ppm of period	
Ramp, triangle		
Frequency range	1 mHz to 100 kHz	
Linearity	< 0.1% of peak output	
Variable symmetry	0.0% to 100.0%	
Pulse		
Frequency range	1 mHz to 5 MHz	
Pulse width (period ≤ 10 s)	40 ns minimum	
	10 ns resolution	
Variable edge time	20 ns to 100 ns	
Overshoot	< 2%	
Jitter (RMS)	300 ps + 0.1 ppm of period	
Noise		
Bandwidth	7 MHz typical	

1 Add 1/10th of output amplitude and offset spec per °C for operation outside the range of 18 to 28 °C

2 Autorange enabled

3 DC offset set to 0 V

4 Spurious output at low amplitude is -75 dBm typical

Waveform characteristics

8K-point arbitrary waveform generator (Option 002)	
Frequency range	1 mHz to 3 MHz
Waveform length	2 to 8 k points
Amplitude resolution	14 bits (including sign)
Sample rate	50 MSa/s
Min. rise/fall time	70 ns typical
Linearity	< 0.1% of peak output
Settling time	< 500 ns to 0.5% of final value
Jitter (RMS)	6 ns + 30 ppm
Non-volatile memory	4 waveforms

Common characteristics

Frequency	
Accuracy ¹	± (10 ppm + 3 pHz) in 90 days
	± (20 ppm + 3 pHz) in 1 year
Resolution	1 µHz (internal)
	1 mHz (user)
Amplitude	
Range	10 mV _{pp} to 10 V _{pp} into 50 Ω
	20 mV _{pp} to 20 V _{pp} into open circuit
Accuracy ^{2, 3} (at 1 kHz)	± 2% of setting
	± 1 mV _{pp}
Units	V _{pp} , V _{rms} , dBm
Resolution	3 digits
DC offset	
Range (peak AC + DC)	± 5 V into 50 Ω
	± 10 V into open circuit
Accuracy ^{2, 3}	± 2% of offset setting
	± 0.5% of amplitude
	± 2 mV
Resolution	3 digits
Main output	
Impedance	50 Ω typical
Isolation	42 V _{pk} maximum to earth
Protection	Short-circuit protected, overload automatically disables main output

¹ Add 1 ppm/°C average for operation outside the range of 18 to 28 °C.

² Add 1/10th of output amplitude and offset spec per °C for operation outside the range of 18 to 28 °C.

³ Autorange enabled.

External frequency reference (Option 001)

Rear panel input	
Lock range	10 MHz \pm 500 Hz
Level	100 mV _{pp} to 5 V _{pp}
Impedance	1 k Ω , typical
Lock time	< 2 seconds
Rear panel output	
Frequency	10 MHz
Level	632 mV _{pp} (0 dBm), typical
Impedance	50 Ω , typical AC coupled
Phase offset	
Resolution	+360° to -360°
Resolution	0.001°
Accuracy	20 ns

Modulation

AM	
Carrier waveforms	Sine, Square
Source	Internal/external
Internal modulation	Sine, Square, Ramp, Triangle, Noise, Arb ¹ (2 MHz to 20 kHz)
Depth	0.0% to 120.0%
FM	
Carrier waveforms	Sine, Square
Source	Internal/External
Internal modulation	Sine, Square, Ramp, Triangle, Noise, Arb ¹ (2 MHz to 20 kHz)
Deviation	DC to 5 MHz
PWM	
Carrier waveforms	Pulse
Source	Internal/External
Internal modulation	Sine, Square, Ramp, Triangle, Noise, Arb ¹ (2 MHz to 20 kHz)
Deviation	0% to 100% of pulse width
External modulation input (for AM, FM, PWM)	
Voltage range	\pm 5 V full scale
Input impedance	5 k Ω typical
Bandwidth	DC to 20 kHz
Sweep	
Waveforms	Sine, Square, Ramp
Type	Linear or Logarithmic
Direction	Up or Down
Sweep time	1 ms to 500 s
Trigger source	Single, External or Internal
Marker	Falling edge of sync signal (programmable frequency)
Burst ²	
Waveforms	Sine, Square, Ramp
Type	Counted (1 to 50,000 cycles), Infinite, Gated
Start/stop phase	+360° to -360°
Internal period	1 μ s to 500 s
Gate source	External trigger
Trigger source	Single, External or Internal

¹ Only available if Option 002 is installed

² Sine and square waveforms above 3 MHz are allowed only with an "infinite" burst count

Trigger characteristics

Trigger input			
Input level	TTL compatible		
Slope	Rising or Falling, selectable		
Pulse width	> 100 ns		
Input impedance	> 10 k Ω , DC coupled		
Latency	< 500 ns		
Jitter (rms)	6 ns (3.5 ns for pulse)		
Trigger output			
Level	TTL compatible into ≥ 1 k Ω		
Pulse width	> 400 ns		
Output impedance	50 Ω typical		
Maximum rate	1 MHz		
Fanout	≤ 4 Keysight 33210As (or equivalent)		
Programming times (typical)			
Configuration times	USB	LAN	GPIOB
Function change	120 ms	120 ms	120 ms
Frequency change	2 ms	3 ms	2 ms
Amplitude change	30 ms	30 ms	2 ms
Select user arb	130 ms	130 ms	2 ms
Arb download times (Option 002)	Binary transfer		
	USB	LAN	GPIOB
2 k points	5 ms	9 ms	10 ms
4 k points	8 ms	15 ms	20 ms
8 k points	14 ms	27 ms	40 ms
General			
Power supply	Cat II 100 to 240 V @ 50/60 Hz (-5%, +10%) 100 to 120 V @ 400 Hz ($\pm 10\%$)		
Power consumption	50 VA max		
Operating environment	IEC 61010 Pollution Degree 2 Indoor Location		
Operating temperature	0 to 55 $^{\circ}$ C		
Operating humidity	5% to 80% RH, non-condensing		
Operating altitude	Up to 3000 meters		
Storage temperature	-30 to 70 $^{\circ}$ C		
State storage memory	Power off state automatically saved Four user-configurable stored states		
Interface	LAN LXI-C Ethernet 10/100 USB 2.0, GPIOB		
Language	SCPI – 1993, IEEE-488.2		
Bench top dimensions	261.1 mm x 103.8 mm x 303.2 mm (W x H x D)		
Rack mount dimensions	212.88 mm x 88.3 mm x 272.3 mm (W x H x D)		
Weight	3.4 kg (7.5 lbs)		
Safety and EMC Regulatory	MIL-461C Refer to Declaration of Conformity for the latest revisions of regulatory compliance at: www.keysight.com/go/conformity		
Vibration and shock	MIL-T-28800, Type III, Class 5		
Acoustic noise	30 dBA		
Warm-up time	1 hour		

Ordering Information

Keysight 33210A

10 MHz function/arbitrary waveform generator.

Options

Option	Description
Opt. 001	External timebase reference
Opt. 002	8K-point arbitrary waveform generator
Opt. A6J	ANSI Z540 calibration
Opt. AB0	Taiwan: Chinese manual
Opt. AB1	Korea: Korean manual
Opt. AB2	China: Chinese manual
Opt. ABA	English: English manual
Opt. ABD	Germany: German manual
Opt. ABF	France: French manual
Opt. ABJ	Japan: Japanese manual
Opt. PLG	Continental European power cord

Other accessories

Option	Description
34131A	Carrying case
34161A	Accessory pouch
34190A	Rackmount kit
34191A	Dual flange kit, 2U
34194A	Dual lock link kit

Keysight enables innovators to push the boundaries of engineering by quickly solving design, emulation, and test challenges to create the best product experiences. Start your innovation journey at www.keysight.com.