

# Keysight 34420A

## NanoVolt/Micro-Ohm Meter

- 7½ digit resolution
- 100 pV, 100 nΩ sensitivity
- 1.3 nVrms, 8 nVpp noise performance
- Built-in low noise 2 channel scanner
- Direct SPRT, RTD, Thermistor, and Thermocouple measurements

Data Sheet



## Nanovolt Performance at a Microvolt Price

The Keysight Technologies, Inc. 34420A nanoVolt/micro-Ohm meter is a high-sensitivity multimeter optimized for performing low-level measurements. It combines low-noise voltage measurements with resistance and temperature functions, setting a new standard in low-level flexibility and performance.

## Take the Uncertainty Out of Your Low-Level Measurements

Low-noise input amplifiers and a highly tuned input protection scheme bring reading noise down to 8 nVpp. Combine this with 7½ digits of resolution, selectable analog and digital filtering, 2 ppm basic 24-hour dcV accuracy, and a shielded, copper pin connector and you've got accurate, repeatable measurements you can count on.

## Two Input Channels

An integral two-channel programmable scanner simplifies voltage comparisons. Built-in ratio and difference functions enable automated two channel measurements without the need for an external nanoVolt scanner. Both channels share the same low noise specifications to ensure accurate comparisons.

## Built-In Resistance and Temperature

The 34420A combines its low-noise nano-Volt input circuits with a high-stability current source to provide precise low-level resistance measurements – no more hassling with the cost and complexity of an external current source. Three resistance modes are included:

- Standard
- Low-power
- Voltage-limited for dry-circuit testing

Offset compensation is also provided to minimize thermal EMFs and associated errors.

## SPRT Measurements

Built-in ITS-90 conversion routines accept the calibration coefficients from your SPRT probe for direct temperature measurement and conversion. Thermocouples, thermistors, and RTDs are also supported.

## Unequaled Versatility

The 34420A gives you the versatility to tackle your most challenging tasks, both on the benchtop and in your automated system. Standard features include RS-232 and GPIB interfaces, SCPI and Keithley 181 programming language, 1024-reading memory, scaling and statistics, and a chart recorder analog output.

## Keysight IntuiLink: Easy Data Access

The included Keysight IntuiLink software allows your captured data to be put to work easily, using PC applications such as Microsoft Excel or Word to analyze, interpret, display, print, and document the data you get from the 34420A. You can specify the meter setup and take a single reading or log data to the Excel spreadsheet in specified time intervals. To find out more about IntuiLink visit [www.keysight.com/find/intuilink](http://www.keysight.com/find/intuilink).

## Quality You Can Count On

The 34420A gives you the quality and reliability you expect from Keysight Technologies. From the Keysight proven >150,000 hour Mean Time Between Failure, to its standard 1-year warranty, Keysight stands behind you to bring a new level of confidence to your low-level measurements.

## Specifications

Accuracy Specifications  $\pm$ (% of reading + % of range)<sup>1</sup>

Function	Range <sup>2</sup>	Test Current	24-Hour 23 °C $\pm$ 1 °C	90 Day 23 °C $\pm$ 5 °C	1 Year 23 °C $\pm$ 5 °C	Temperature Coefficient 28 °C–55 °C	Maximum per Lead Resistance
dc Voltage	1.000000 mV <sup>3</sup>		0.0025 + .0020	0.0040 + .0020	0.0050 + .0020	0.0004 + .0001	
	10.000000 mV <sup>3</sup>		0.0025 + .0020	0.0040 + .0002	0.0050 + .0003	0.0004 + .0001	
	100.000000 mV		0.0015 + .0003	0.0030 + .0004	0.0040 + .0004	0.0004 + .00006	
	1.0000000 V		0.0010 + .0003	0.0025 + .0004	0.0035 + .0004	0.0004 + .00004	
	10.000000 V		0.0002 + .0001	0.0020 + .0004	0.0030 + .0004	0.0001 + .00002	
	100.000000 V <sup>4</sup>		0.0010 + .0004	0.0025 + .0005	0.0035 + .0005	0.0004 + .00005	
Resistance <sup>5</sup>	1.0000000 $\Omega$	10 mA	0.0015 + .0002	0.0050 + .0002	0.0070 + .0002	0.0005 + .00002	1 $\Omega$
	10.000000 $\Omega$	10 mA	0.0015 + .0002	0.0040 + .0002	0.0060 + .0002	0.0005 + .00001	1 $\Omega$
	100.000000 $\Omega$	10 mA	0.0015 + .0002	0.0040 + .0002	0.0060 + .0002	0.0005 + .00001	10 $\Omega$
	1.0000000 K $\Omega$	1 mA	0.0015 + .0002	0.0040 + .0002	0.0060 + .0002	0.0005 + .00001	100 $\Omega$
	10.000000 K $\Omega$	100 $\mu$ A	0.0015 + .0002	0.0040 + .0002	0.0060 + .0002	0.0005 + .00001	1 K $\Omega$
	1.0000000 M $\Omega$	10 $\mu$ A	0.0015 + .0003	0.0040 + .0004	0.0060 + .0004	0.0005 + .00002	1 K $\Omega$
	100.000000 K $\Omega$	5 $\mu$ A	0.0020 + .0003	0.0050 + .0004	0.0070 + .0004	0.0006 + .00003	1 K $\Omega$
Low Power Resistance <sup>5</sup>	1.0000000 $\Omega$	10 mA	0.0015 + .0002	0.0050 + .0002	0.0070 + .0002	0.0005 + .00002	1 $\Omega$
	10.000000 $\Omega$	10 mA	0.0015 + .0002	0.0040 + .0002	0.0060 + .0002	0.0005 + .00001	1 $\Omega$
	100.000000 $\Omega$	1 mA	0.0015 + .0002	0.0040 + .0002	0.0060 + .0002	0.0005 + .00001	10 $\Omega$
	1.0000000 K $\Omega$	100 $\mu$ A	0.0015 + .0002	0.0040 + .0002	0.0060 + .0002	0.0005 + .00001	100 $\Omega$
	10.000000 K $\Omega$	10 $\mu$ A	0.0015 + .0004	0.0040 + .0004	0.0060 + .0004	0.0005 + .00001	1 K $\Omega$
	1.0000000 M $\Omega$	5 $\mu$ A	0.0015 + .0012	0.0040 + .0015	0.0060 + .0015	0.0005 + .00003	1 K $\Omega$
	100.000000 K $\Omega$	5 $\mu$ A	0.0020 + .0003	0.0050 + .0004	0.0070 + .0004	0.0006 + .00003	1 K $\Omega$
Voltage Limited Resistance <sup>5,6</sup>	10.000000 $\Omega$	1 mA	0.0020 + .0002	0.0050 + .0002	0.0070 + .0002	0.0005 + .00002	1 $\Omega$
	100.000000 $\Omega$	100 $\mu$ A	0.0025 + .0002	0.0050 + .0002	0.0070 + .0002	0.0005 + .00002	5 $\Omega$
Channel 1 / Channel 2 (dcV Ratio)	Ratio Error in % = Channel 1 accuracy in % + Channel 2 accuracy in %						
Channel 1–Channel 2 (dcV Difference)	Difference Error = Channel 1 (% of reading + % of range) + Channel 2 (% of reading + % of range)						
Temperature (resolution = 0.001 °C)							
SPRT <sup>7</sup>	SPRT Probe Accuracy + 0.003°C						
RTD	RTD Probe Accuracy + 0.05°C						
Thermistor	Thermistor Probe Accuracy + 0.1°C						
Thermocouple <sup>8</sup>	Thermocouple Probe Accuracy + 0.2°C						

### DC Voltage Noise<sup>9</sup>

Range	Observational Period		
	2-Minute RMS Noise	2-Minute Peak-Peak Noise	24-Hour Peak-Peak Noise
1 mV	1.3 nVrms	8 nVpp	12 nVpp
10 mV	1.5 nVrms	10 nVpp	14 nVpp
100 mV	10 nVrms	65 nVpp	80 nVpp
1 V	100 nVrms	650 nVpp	800 nVpp
10 V	450 nVrms	3 $\mu$ Vpp	3.7 $\mu$ Vpp
100 V	11 $\mu$ Vrms	75 $\mu$ Vpp	90 $\mu$ Vpp

### DC Voltage Noise vs Source Resistance<sup>10</sup>

Source Resistance	Noise	Analog Filter	Digital Filter
0 $\Omega$	1.3 nVrms	Off	Med
1000 $\Omega$	1.7 nVrms	Off	Med
1k $\Omega$	4 nVrms	Off	Med
10k $\Omega$	13 nVrms	Off	Med
100k $\Omega$	41 nVrms	Off	Med
1M $\Omega$	90 nVrms	Off	Med

- Specifications are for Channel 1 or Channel 2, after 2-hour warm-up, resolution at 7.5 digits (100 NPLC), with FILTERS off. RESISTANCE specifications are for 4-wire Ohms or 2-wire ohms using Null. Without Null, add 0.2 Ohms additional error in 2-wire Ohms function. For Analog Filter ON, add 0.002% of reading.
- 20% overrange on all ranges except 5% on Voltage Limited Resistance.
- After using Math Null. If Null is not used add 100 nanoVolts.
- Channel 1 only.
- Channel 1 only. Resistance measurements, for NPLC <1, add 160  $\mu\Omega$  rms noise.
- Voltage limit can be set to 20 mV (default), 100 mV, or 500 mV. Measured resistance plus Channel 1 HI and LO lead resistance is limited to 10.5  $\Omega$  on the 10  $\Omega$  range and 105  $\Omega$  on the 100  $\Omega$  range.
- For 25  $\Omega$  SPRT with triple-point of water check within the last 4 hours. Without the triple-point of water check, add 0.013°C for 24 hours, add 0.035°C for 90 day, and add 0.055°C for 1 year specifications.
- For fixed reference junction. Add 0.3°C for external reference junction, add 2.0°C for internal reference junction.
- After a 2-hour warm-up,  $\pm$  1°C, 6.5 digits (10 PLC) with Analog Filter Off and Digital Filter Medium (50 reading average). 2-minute rms and 24-hour noise typical. For measurements using 0.02 or 0.2 NPLC, add 800 nV rms noise.
- Typical noise behavior for Ch 1 or Ch 2, after 2 hour warm-up, 6.5 digits (10 PLC), 2 minute observation period on 1 mV range. For peak-to-peak noise, multiply rms noise by 6.

## Measurement Characteristics

**DC Voltage**

Measurement Method:  
Continuously integrating multi-slope III  
A-D Converter

A-D Linearity:  
0.00008% of reading + 0.00005% of range

Input Resistance:  
100V (Ch1 only): 10 M $\Omega$  +- 1%  
1mV through 10V: > 10 G $\Omega$ , in parallel with < 3.6 nF

Input Bias Current: <50 pA at 25 °C

Injected Current: <50 nA pp at 50 or 60 Hz

Input Protection:  
150 V peak any input terminal  
to Channel 1 LO, continuous

Channel-to-channel switching error (typical): 3 nV

Channel Isolation:  
Isolation between input channels >10<sup>10</sup>  $\Omega$

Earth Isolation:  
350 V peak any input terminal to earth.  
Impedance from any input terminal to earth  
is >10 G $\Omega$  and <400 pF

Maximum Voltage:  
Channel 1 LO to Channel 2 LO, 150V peak

**Resistance**

Measurement Method:  
Selectable 4-wire or 2-wire ohms. Current  
Source referenced to Channel 1 LO input

Offset Compensation:  
Used on all ranges except 100 k $\Omega$  and 1 M $\Omega$ .  
Can be turned off if desired

Protection: 150 V peak

Open Circuit Voltage:  
For Resistance and Low Power Resistance  
<14 V, 20 mV, 100 mV, 500 mV selectable clamp

**Temperature**

SPRT:  
ITS-90 calibrated temperature with the range  
of -190°C to +660°C

Thermocouple:  
ITS-90 conversions of Type B, E, J, K, N, R, S, T

Thermistor: 5 k $\Omega$

RTD: Type  $\alpha$  = .00385 and  $\alpha$  = .00392. R0 from  
4.9  $\Omega$  to 2.1 k $\Omega$ . ITS -90 (IEC-751) Callendar  
Van Dusen conversion.

**Measurement Noise Rejection 60 (50) Hz<sup>1</sup>**

dc CMRR: 140 dB  
ac CMRR: 70 dB

Operating Characteristics<sup>4</sup>

Function	Digits	Integration Time	Readings/s <sup>5</sup>
dcV	7-1/2	200 plc	.15 (.125)
Thermocouple	7-1/2	100 plc	.3 (.25)
	6-1/2	20 plc	1.5 (1.25)
	6-1/2	10 plc	3 (2.5)
	5-1/2	1 plc	25 (20.8)
	5-1/2	0.2 plc	100 (100)
	4-1/2	0.02 plc	250 (250)
Resistance	7-1/2	200 plc	.075 (.062)
dcV1/DCV2	7-1/2	100 plc	.15 (.125)
dcV 1-2	6-1/2	20 plc	.75 (.625)
RTD	6-1/2	10 plc	1.5 (1.25)
Thermistor	5-1/2	1 plc	12.5 (10.4)
0.2 plc	50 (50)		
	4-1/2		
0.02 plc	125 (125)		

Integration Time	Normal Mode Rejection <sup>2</sup>
200 plc/3.335 s (4 s)	110 dB <sup>3</sup>
100 plc/1.675 s (2 s)	105 dB <sup>3</sup>
20 plc/334 ms (400 ms)	100 dB <sup>3</sup>
10 plc/167 ms (200 ms)	95 dB <sup>3</sup>
2 plc/33.3 ms (40 ms)	90 dB
1 plc/16.7 ms (20 ms)	60 dB
<1 plc	0

**System Speeds<sup>6</sup>**

Configuration Rates: 26/s to 50/s  
Autorange Rate (Volts): >30/s  
ASCII reading to RS-232: 55/s  
ASCII reading to GPIB: 250/s  
Max. Internal Trigger Rate: 250/s  
Max. Ext. Trig. Rate to Memory: 250/s

**Triggering and Memory**

Reading HOLD Sensitivity:  
10%, 1%, 0.1%, or 0.01% of range  
Samples/Trigger: 1 to 50,000  
Trigger Delay: 0 to 3600 s; 10  $\mu$ s step size  
External Trigger Delay: <1 ms  
External Trigger Jitter: <500  $\mu$ s  
Memory: 1024 readings

**Math Functions**

NULL (Channel 1 dcV, Channel 2 dcV,  
Difference, Resistance, Temperature)

STATS (Min, Max, Average, Peak-Peak,  
Standard Deviation, Number of readings)

SCALE (Allows linear scaling as  $y = mx+b$ )

CHART NULL (Establishes zero for rear panel  
output)

**Filter (Analog or Digital or Both)**

Analog:  
Low pass 2 pole @ 13Hz, available for dcV  
on 1 mV, 10 mV, 100 mV range

Digital:  
Moving average filter, 10 (fast), 50 (medium),  
or 100 (slow) reading averages.

**Chart Out (Analog Out)**

Maximum output:  $\pm$  3V

Resolution: 16 bits

Accuracy:  $\pm$  0.1% of output + 1 mV

Output Resistance: 1 k $\Omega$   $\pm$  5%

Update rate: once per reading

Span and Offset: Adjustable

**Standard Programming Languages**

SCPI (IEEE 488.2), Keithley 181

**Accessories Included**

4 ft low thermal cable with copper spade lugs,  
Kelvin clip set, 4-wire shorting plug, user's  
manual, service manual, test report, contact  
cleaner, and power cord.

1 For 1 k $\Omega$  unbalanced in LO lead.

2 For power line frequency  $\pm$  - 0.1%, Filters OFF.  
For Digital Filter slow add 20 db, for medium or  
fast add 10 db for NPLC<sup>3</sup> 1.

3 For power line frequency  $\pm$  - 1%, use 80 db, for  
 $\pm$  - 3% use 60 db.

4 Speeds are for delay 0, Display OFF, Filters OFF,  
Offset Compensation OFF.

5 Reading speeds for 60 Hz or (50 Hz), 100 mV  
through 100 V ranges. 1 mV range 30/s MAX, 10  
mV range 170/s MAX, thermocouple 120/s MAX.

6 Speeds are for NPLC 0.02, Delay 0, Display OFF,  
Chart Out OFF.

## General Specifications

Front Panel Connection:  
Shielded, low thermal, 99% copper contacts.

Power Supply:  
100V/120V/220V(230V)/240V +- 10%.

Power Line Frequency:  
45 Hz to 66 Hz and 360 Hz to 440 Hz.  
Automatically sensed at power-on.

Power Consumption:  
25VA peak (10W average).

Operating Environment:  
Full accuracy for 0 °C to 55 °C. Full accuracy to 80% R.H. up to 30 °C.

Storage Environment:  
-40 °C to 75 °C.

Size: 254.4 mm W x 374.0 mm L x 103.6 mm H  
(10.02" W x 14.72" L x 4.08" H)

Weight: 3 kg (6.5 lbs).

Safety:  
Designed to CSA, UL-1244, IEC-1010.  
RFI and ESD: CISPR 11.

## Ordering Information

Includes low thermal input cable (34102A), low thermal shorting plug (34103A), Kelvin clip set (11062A), calibration certificate, power cord. Also includes CD with: IntuiLink software, IVI and VXI PnP drivers, user's guide, service guide, and data sheet.

### Options

34420A-ABA English localization  
34420A-ABD German localization:  
translated operating manual  
34420A-ABF French localization:  
translated operating manual  
34420A-ABJ Japanese localization:  
translated operating manual  
34420A-A6J ANSI Z540 compliant  
calibration

## Accessories

34102A Low-thermal input cable (four conductor) with copper spade lugs  
34103A Low-thermal shorting plug  
34104A Low-thermal input connector  
34131A Transit Case  
34161A Accessory pouch  
34190A Rackmount Kit: designed for use with only one instrument, mounted on either the left or the right side of the rack.  
34191A 2U Dual Flange Kit: secures the instrument to the front of the rack. This kit can be used with the  
34194A Dual Lock Link Kit to mount two half-width, 2U height instruments side-by-side.  
34194A Dual Lock Link Kit: recommended for side-by-side combinations and includes links for instruments of different depths. This kit can be used with the 34191A 2U Dual Flange Kit to mount two half-width, 2U height instruments side-by-side.

**myKeysight**

**myKeysight**

[www.keysight.com/find/mykeysight](http://www.keysight.com/find/mykeysight)

A personalized view into the information most relevant to you.



[www.axistandard.org](http://www.axistandard.org)

AdvancedTCA® Extensions for Instrumentation and Test (AXIe) is an open standard that extends the AdvancedTCA for general purpose and semiconductor test. Keysight is a founding member of the AXIe consortium. ATCA®, AdvancedTCA®, and the ATCA logo are registered US trademarks of the PCI Industrial Computer Manufacturers Group.



[www.lxistandard.org](http://www.lxistandard.org)

LAN eXtensions for Instruments puts the power of Ethernet and the Web inside your test systems. Keysight is a founding member of the LXI consortium.

**Three-Year Warranty**

[www.keysight.com/find/ThreeYearWarranty](http://www.keysight.com/find/ThreeYearWarranty)

Keysight's commitment to superior product quality and lower total cost of ownership. The only test and measurement company with three-year warranty standard on all instruments, worldwide.



**Keysight Assurance Plans**

[www.keysight.com/find/AssurancePlans](http://www.keysight.com/find/AssurancePlans)

Up to five years of protection and no budgetary surprises to ensure your instruments are operating to specification so you can rely on accurate measurements.



[www.keysight.com/quality](http://www.keysight.com/quality)

Keysight Technologies, Inc.  
DEKRA Certified ISO 9001:2008  
Quality Management System



**Keysight Channel Partners**

[www.keysight.com/find/channelpartners](http://www.keysight.com/find/channelpartners)

Get the best of both worlds: Keysight's measurement expertise and product breadth, combined with channel partner convenience.

ATCA®, AdvancedTCA®, and the ATCA logo are registered US trademarks of the PCI Industrial Computer Manufacturers Group

[www.keysight.com/find/34420A](http://www.keysight.com/find/34420A)

For more information on Keysight Technologies' products, applications or services, please contact your local Keysight office. The complete list is available at: [www.keysight.com/find/contactus](http://www.keysight.com/find/contactus)

**Americas**

Canada	(877) 894 4414
Brazil	55 11 3351 7010
Mexico	001 800 254 2440
United States	(800) 829 4444

**Asia Pacific**

Australia	1 800 629 485
China	800 810 0189
Hong Kong	800 938 693
India	1 800 112 929
Japan	0120 (421) 345
Korea	080 769 0800
Malaysia	1 800 888 848
Singapore	1 800 375 8100
Taiwan	0800 047 866
Other AP Countries	(65) 6375 8100

**Europe & Middle East**

Austria	0800 001122
Belgium	0800 58580
Finland	0800 523252
France	0805 980333
Germany	0800 6270999
Ireland	1800 832700
Israel	1 809 343051
Italy	800 599100
Luxembourg	+32 800 58580
Netherlands	0800 0233200
Russia	8800 5009286
Spain	0800 000154
Sweden	0200 882255
Switzerland	0800 805353
	Opt. 1 (DE)
	Opt. 2 (FR)
	Opt. 3 (IT)
United Kingdom	0800 0260637

For other unlisted countries:  
[www.keysight.com/find/contactus](http://www.keysight.com/find/contactus)  
(BP-07-01-14)

